


|                   |                | Specifiche tecniche  |
|-------------------|----------------|--|
|                   | Image          |    |
|                   | Model          | HB-DVR5108E-D-V2H  |
|                   | Main Chipset   | Hi3521A  |
|                   | RAM            | 1GB  |
|                   | ROM            | 128MB  |
| Decoding          | Compression    | H.264  |
|                   | Resolution     | 8*4MP@6fps(48fps,manual)<br>8*3MP@8fps(64fps,manual)<br>or 8*1080P@15fps(120fps,manual)<br>or 4*1080P@30fps(120fps,automatic)<br>or 8*720P@30fps  8*960H@30FPS |
|                   | Playback       | All Ch. playback at the same time  |
| Video/Audio Input | IP Video Input | 2CH@4MP realtime ;<br>input bandwidth:60Mbps   |
|                   | 5 in 1 input   | AHD@4MP / TVI@3MP / CVI@2MP / IP@4MP   |
|                   | Video input    | 8  |
|                   | Audio input    | 1*RCA  |

|                           |                            |                             |
|---------------------------|----------------------------|-----------------------------|
| <b>Video/Audio Output</b> | <b>Video output</b>        | 0                           |
|                           | <b>Audio output</b>        | 1*RCA                       |
|                           | <b>Video loop output</b>   | 0                           |
|                           | <b>Video matrix output</b> | 0                           |
|                           | <b>VGA(DB15)</b>           | 1                           |
|                           | <b>HDMI</b>                | 1                           |
|                           | <b>SPOT output</b>         | 1                           |
| <b>HDD</b>                | <b>Max capacity</b>        | 4TB                         |
|                           | <b>RAID</b>                | N/A                         |
|                           | <b>SATA</b>                | 1                           |
| <b>interface</b>          | <b>Intercom input</b>      | 0 ( audio input multiplex ) |
|                           | <b>Intercom output</b>     | 0 ( audio out multiplex )   |
|                           | <b>USB</b>                 | 2(back panel)               |
|                           | <b>eSATA</b>               | N/A                         |
|                           | <b>USB ex-recorder</b>     | Support                     |
|                           | <b>RJ45</b>                | 100M                        |
|                           | <b>Alarm in</b>            | 4                           |
|                           | <b>Alarm out</b>           | 1                           |

|              |                           |                   |
|--------------|---------------------------|-------------------|
|              | <b>RS232</b>              | 0                 |
|              | <b>RS485</b>              | 1 ( half-duplex ) |
|              | <b>UTC</b>                | Support           |
|              | <b>IR extend</b>          | N/A               |
|              | <b>IR</b>                 | N/A               |
| <b>Other</b> | <b>+12V Alarm out</b>     | 1                 |
|              | <b>Power</b>              | DC 12V 24W        |
|              | <b>Power switch</b>       | 0                 |
|              | <b>Mouse</b>              | small mouse       |
|              | <b>CE Certification</b>   | √                 |
|              | <b>FCC Certification</b>  | √                 |
|              | <b>RoHS Certification</b> | √                 |